

Electronic Instrumentation

Problem sheet: SI

2011/2012 module 2

P. Stallinga



MIEET 3º ano

1) The relaxation time of an electronic circuit is given by the values of resistance and capacitance. Discuss, on basis of a units analysis, if the relation between these values and the relaxation time is $\tau = RC$ or $\tau = 1/RC$. The table below shows the standard S.I. units

<i>quantity</i>	<i>unit</i>	<i>symbol</i>
Length	meter	m
Mass	kilo	kg
Time	second	s
Electrical current	ampere	A
Thermodynamic temperature	kelvin	K
Quantity of matter	mole	mol
Luminous intensity	candela	cd

2) Which equation is correct?

a) Thermal voltage

$$V_T = kT/q$$

$$V_T = q/kT$$

b) Energy of a charged capacitor

$$E = C^2 V/2$$

$$E = CV^2/2$$

c) Power dissipation

$$P = I^2/R$$

$$P = V^2/R$$

$$P = I^2 R$$

$$P = V^2 R$$

3) What is the energy of a 10 μF capacitor charged to 1 V? Check the units of your equation.